

TXS-1800HSE - Microphone Transmitter



Multifrequency pocket transmitter, 1.8 GHz,
with UHF PLL technology.

- Suitable for combination with headband microphone or earband microphone with 3-pole mini XLR connector
- 192 selectable UHF frequencies (1,785-1,800 MHz) in 16 groups with 12 channels each, can be synchronised with receiver TXS-1800 via ADL function
- Adjustable sensitivity (0 dB, -3 dB, -6 dB)
- LCD for indicating frequency, gain setting and battery status
- Transmitting power: 10 mW (EIRP)
- Mute function
- Belt clip
- Power supply via 2 x 1.5 V battery AA size (not supplied)

There are restrictions or requirements within the EU!

Please read the notes regarding wireless systems in the section "IMPORTANT INFORMATION"!

Technical data:

| | |
|----------------------------|---------------------------|
| Multifrequency | : 1 |
| General information | : |
| Description | : pocket transmitter |
| Carrier frequency range | : 1,785-1,800 MHz |
| Audio frequency range | : 60-16,000 Hz |
| Channels | : 1 |
| THD | : - |
| Dynamic range | : - |
| Latency | : |
| RF S/N ratio | : - |
| Operating time | : ? 8 h |
| Admiss. ambient temp. | : 0-40 °C |
| Power supply | : - |
| Dimensions | : - |
| Total weight | : - |
| Connections | : - |
| Specifications transmitter | : |
| Transmitting power | : 10 mW |
| Operating range | : - |
| Power supply transmitter | : 2 x 1.5 V batt. AA size |
| Width transmitter | : 64 mm |
| Height transmitter | : 102 mm |
| Depth transmitter | : 28 mm |
| Weight transmitter | : 118 g |
| Connections transmitter | : 1 x 3-pole mini XLR |
| Specifications receiver | : - |
| Audio signal receiver | : - |
| Power supply receiver | : - |
| Width receiver | : - |
| Height receiver | : - |
| Depth receiver | : - |
| Weight receiver | : - |
| Connections receiver | : - |