

## FGA-22S - REM generator



Transformer with switching voltage generation,  
for car radios with bridge power amplifier only, for connecting speaker outputs of a car radio to the line inputs  
of an amplifier.

- For operation with car audio systems which do not feature a switching voltage output
- Switching voltage (REM) is generated independently of the audio signal, even when the music stops
- Internal ground separation
- Screw terminals, gold-plated RCA jacks
- Max. input power: 20 W
- Input/output impedance: 20 kOhm/10 kOhm
- Frequency range: 20-30,000 Hz
- THD: < 0.01%
- Power supply: DC 12 V/25 mA
- 43 x 27 x 100 mm, 70 g

## Technical data:

Description	: transformer
Frequency range	: 20-30,000 Hz
Control range	: -
Control frequencies	: -
Input signal	: -
Input sensitivity	: -
Input impedance	: 20 kOhm
Output signal	: -
Output impedance	: 10 kOhm
Gain	: -
Phantom power	: -
Compression	: -
Gate ratio	: -
Crossover frequency	: -
High-pass filter	: -
Low cut	: -
Transmission ratio	: -
S/N ratio	: -
Channel separation	: -
THD	: < 0.01%
Admiss. ambient temp.	: 0-40 °C
Power supply	: DC 12V/25 mA
Dimensions	: 43 x 27 x 100 mm
Weight	: 60 g
Inputs	: screw terminals
Outputs	: 1 x RCA L/R
Other features	: -