



## NTE-1 - Audio Transformer



Audio transformer 1:1 for microphone signals,  
from NEUTRIK.

- Very compact design, e.g. also suitable for installation into connector housings
- Unshielded version with bare wire connections (70 mm)
- Wideband version
- Balance adjustment
- Galvanic isolation to avoid/eliminate hum loops
- Max. input voltage: 550 mV (1% THD/50 Hz)

When installing unshielded transformers into units with interference fields (e.g. power transformers), attention has to be paid to respective shielding measures.

## Technical data:

Description	: transformer
Frequency range	: 20-20,000Â Hz
Control range	: -
Control frequencies	: -
Input signal	: 50 mV
Input sensitivity	: -
Input impedance	: 200 Ohm
Output signal	: -
Output impedance	: 2 kOhm
Gain	: -
Phantom power	:
Compression	: -
Gate ratio	: -
Crossover frequency	: -
High-pass filter	: -
Low cut	: -
Transmission ratio	: 1:1
S/N ratio	: -
Channel separation	: -
THD	: -
Admiss. ambient temp.	: -
Power supply	: -
Dimensions	: 14 x 11 x 12Â mm(w/o cable)
Weight	: 6 g
Inputs	: -
Outputs	: -
Other features	: -
Width	: 14 mm
Height	: 11 mm
Depth	: 12 mm
Length	: -
Rack units, RU	: -
Weight	: 6.1 g