

## TXA-800HSE - Microphone Transmitter



**Trådløs lommesender**, med UHF PLL teknologi. Matcher transportable forstærkersystemer i TXA-1000, TXA-800 og TXA-800R serien.

- 1 headset-mikrofon (omnidirectional karakteristik), 1 knaphulsmikrofon (cardioid karakteristik)
- 16 UHF frekvenser (863,1-864,9 MHz)
- Metalkabinet
- Mikrofontilslutning via 3-polet mini XLR
- Audio line-indgang via 3,5 mm stereo minijack
- 3-trins justerbar følsomhed
- Mute funktion
- Baggrundsbelyst LCD-indikator for kanal/frekvens og batteristatus
- Sendestyrke: 10 mW (EIRP)
- Strømforsyning: 2 x 1,5 V batteri, størrelse AA (medfølger ikke)
- Bælteclip

**Licensfri i EU.tastenwelt 02/2008**

"The use of the headset is interesting for keyboard players."

## Technical data:

Multifrequency	: 1
Tie clip microphone	: 1
Headband microphone	: 1
General information	:
Description	: pocket transmitter
Carrier frequency range	: 863.1-864.9 MHz
Audio frequency range	: 70-16,000 Hz
Channels	: 1
THD	: -
Dynamic range	: -
Latency	:
RF S/N ratio	: -
Operating time	: -
Admiss. ambient temp.	: 0-40 °C
Power supply	: -
Dimensions	: -
Total weight	: -
Connections	: -
Specifications transmitter	:
Transmitting power	: 10 mW
Operating range	: 30 m
Power supply transmitter	: 2 x 1.5 V batt. AA size
Width transmitter	: 65 mm
Height transmitter	: 95 mm
Depth transmitter	: 30 mm
Weight transmitter	: 110 g
Connections transmitter	: 1 x 3-pole mini XLR
Specifications receiver	: -
Audio signal receiver	: -
Power supply receiver	: -
Width receiver	: -
Height receiver	: -
Depth receiver	: -
Weight receiver	: -
Connections receiver	: -