

## SA-160BT - Amplifier



**Mini stereoforstærker, 2 x 30 W**, med Bluetooth interface, NFC og fjernbetjening.

- Integreret Hi-Fi forstærker
- Til højttalere med 8 Ohm impedans
- Volumenkontrol med indbygget kildevælger, LED-indikator
- Near Field Communication (NFC)
- Forgylde højttalerterminaler
- 1 stereoindgang, phonostik L/R
- 1 line-udgang, 3,5 mm stereostik
- Fast antenne
- Metalkabinet
- Strømforsyning medfølger

## Technical data:

Bluetooth	: 1
Peak output power	: 2 x 60 W
Power rating	: 60 W
Power rating at 2 Ohm	: -
Power rating at 4 Ohm	: -
Power rating at 8 Ohm	: 2 x 30 W
Power rating at 16 Ohm	: -
Power rating at 100 V	: -
Power rating with 4 Ohm bridged operation	: -
Power rating with 8 Ohm bridged operation	: -
Output impedance	: -
Channels	: 2
Zones	: -
Inputs	: 660 mV/10 kOhm
Attenuation factor	: -
Frequency range	: 20-20,000 Hz
Crossover network	: -
Crossover frequency	: -
Integrated limiter	: -
Equalizer bass	: -
Equalizer midrange	: -
Equalizer treble	: -
S/N ratio	: ? 99 dB(A)
Crosstalk attenuation	: -
THD	: -
Phantom power	: -
Mains voltage	: -
Mains frequency	: -
Power consumption, operation	: -
Power consumption, standby	: -
Standby current	: 100 mA
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Width	: 150 mm



Height	: 49 mm
Depth	: 122 mm
Rack units, RU	: -
Weight	: 610 g
Connections	: 1 x RCA L/R (line), 4 x spring-load. speaker term.(speakers)
Packing dimensions (W x H x L)	: 0.21 x 0.07 x 0.3 m
Gross weight	: 1.26 kg
Net weight	: 0.995 kg