

## AKB-160DT - Amplifier Module



### Lad os streame ...

De velkendte og pålidelige forstærkersystemer PA-900 og AKB-160 fås nu med et 2-kanals Dante(tm) modul, som gør dem til Dante(tm) "instreamers" med mangfoldige anvendelsesmuligheder. Forstærkerne kan modtage et digitalt stereosignal eller to monosignaler via RJ45-indgangene. Signalerne konverteres til et analogt lydsignal, forstærkes og streames. Det er således muligt at integrere et analogt højttalersystem i et digitalt Dante netværk.

### PA-forstærkermodule med integreret Dante(tm) modul

- 1 x 40 W
- 100 V output
- Lydløs i brug: blæserfrit kølesystem
- Dante(tm) indgang
- Højttalerudgang via klemterminaler
- Metalkabinet med monteringsbeslag

## Technical data:

100 V	: 1
Fanless	: 1
Dante <sup>(r)</sup>	: 1
Peak output power	: 60 W
Power rating	: 40 W
Power rating at 2 Ohm	: -
Power rating at 4 Ohm	: -
Power rating at 8 Ohm	: -
Power rating at 16 Ohm	: -
Power rating at 100 V	: 40 W
Power rating with 4 Ohm	: -
bridged operation	
Power rating with 8 Ohm	: -
bridged operation	
Output impedance	: -
Channels	: 1
Zones	: 1
Inputs	: network
Attenuation factor	: -
Frequency range	: 17-20,000 Hz
Crossover network	: -
Crossover frequency	: -
Integrated limiter	: -
Equalizer bass	: -
Equalizer midrange	: -
Equalizer treble	: -
S/N ratio	: ? 80 dB
Crosstalk attenuation	: -
THD	: < 1%
Phantom power	: -
Mains voltage	: ~ 230 V
Mains frequency	: 50 Hz
Power consumption, operation	: 75 VA
Power consumption, standby	: -
Standby current	: -
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -

Admiss. ambient temp.	: 0-40 °C
Width	: 213 mm
Height	: 55 mm
Depth	: 238 mm
Rack units, RU	: -
Weight	: 3.2 kg
Connections	: 1 x RJ45 (Dante <sup>(r)</sup> )
Packing dimensions (W x H x L)	: 0.31 x 0.11 x 0.29 m
Gross weight	: 3.68 kg
Net weight	: 3.27 kg