

## DMP-130MIXBT - Audio Player/Mixer



MP3 player and microphone line mixer

With this unit combination, it is possible to mix 3 audio signal sources. The integrated MP3 player can be switched between SD card, USB port and Bluetooth receiver.

- USB storage media can be connected directly
- For SD/MMC cards up to 64 GB, not in the scope of delivery
- Autoplay/single play function
- Repeat function
- Supports directoroty
- 5-band equalizer
- Autostart of last source/replay mode/Equalizer setting
- Alphanumeric display
- Repeat function
- 3 input channels with level control (mic, aux/MP3, line)
- Aux input and microphone input via front panel connection
- 2-way tone control and level control for the master output
- Infrared remote control for MP3 player
- Blue backlit LCD
- 482 mm (19") rack installation

## Technical data:

Description	: MP3 player and microphone line mixer
Media	: MP3, USB, SD, MMC
Frequency range	: 20-20,000 Hz
THD	: < 0.1%
Channel separation	: ? 60 dB
Dynamic range	: ? 96 dB
S/N ratio	: ? 70 dB
Output, analogue	: 2 V (XLR, bal.) 1 V (RCA)
Output, digital, U <sub>pp</sub>	: -
Power supply	: ~; 230 V/50 Hz/20 VA
Mains voltage	: ~; 230 V
Mains frequency	: 50 Hz
Power consumption, operation	: 20 VA
Power consumption, standby	: -
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Dimensions	: 482 x 44 x 165 mm, 1 RU
Dim., player mech.	: -
Dim., control panel	: -
Weight	: 2.36 kg
Connections	: 1 x combo 6.3 mm/XLR (mic/line), 1 x 3.5 mm jack (aux in), 1 x RCA L/R (line in), 1 x RCA L/R (line out),
Packing dimensions (W x H x L)	: 0.195 x 0.116 x 0.555 m
Gross weight	: 3.37 kg