

MA-100/15 - Mike Matching Transformer



Microphone matching transformer, with Hi/Lo switch. With balanced XLR connection as well as 6.3 mm plug, unbalanced, with 15 cm microphone cable.

- Frequency range: 50-15,000 Hz
- Input impedance: 600 Ohm
- Transformation ratio: 1:10/1:1 (1 kHz)

Technical data:

| | |
|--------------------------------|---|
| Description | : Microphone matching transformer |
| Nominal value | : 50-15,000 Hz, 600 Ohm |
| Type | : with Hi/Lo switch |
| Colour | : chrome/black |
| Material | : - |
| Suitable for | : - |
| Power supply | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Dimensions | : - |
| Length | : - |
| Mounting dimensions | : - |
| Weight | : 80 g |
| Connections | : 1 x XLR, bal. 1 x 6.3 mm plug, unbal. |
| Other features | : transformation ratio: 1:10/1:1 (1Â kHz) |
| Packing unit | : 1 |
| Packing dimensions (W x H x L) | : 0.16 x 0.02 x 0.23 m |
| Gross weight | : 0.088 kg |
| Net weight | : 0.08 kg |