DMP-130MIXBT - Audio Player/Mixer



MP3 player and microphone line mixer
With this unit combination, it is possible to mix 3 audio signal sources. The integrated MP3 player can be switched between SD card, USB port and Bluetooth receiver.

- For USB and SD storage media
- Alphanumeric display
- Repeat function
- Preprogrammed sound adjustments
- 3 input channels with level control (mic, aux/MP3, line)
- Aux input and microphone input via front panel connection
- 2-way tone control and level control for the master output
- Infrared remote control for MP3 player
- Blue backlit LCD
- 482 mm (19") rack installation

Technical data:

Description	:	MP3 player and microphone line mixer
Media	:	MP3, USB, SD, MMC
Frequency range	:	20-20,000Â Hz
THD	:	< 0.1%
Channel separation	:	? 60 dB
Dynamic range	:	? 96 dB
S/N ratio	:	? 70 dB
Output, analogue	:	2Â V (XLR, bal.) 1Â V (RCA)
Output, digital, U_{pp}	:	-
Power supply	:	∿ 230Â V/50Â Hz/20Â VA
Mains voltage	:	∼ 230 V
Mains frequency	:	50 Hz
Power consumption, operation	:	20 VA
Power consumption, standby	:	-
Operating voltage (possible alternative)	:	-
Power supply (possible alternative)	:	-
Admiss. ambient temp.	:	0-40Â °C
Dimensions	:	482 x 44 x 165Â mm, 1 RU
Dim., player mech.	:	-
Dim., control panel	:	-
Weight	:	2.36 kg
Connections	:	1 x combo 6.3 mm/XLR (mic/line), 1 x 3.5 mm jack (aux in), 1 x RCA L/R (line in), 1 x RCA L/R (line out),
Packing dimensions (W x H x L)	:	0.195 x 0.116 x 0.555 m
Gross weight	:	3.37 kg