

## PA-1200RDSU - Tuner Module



FM/AM RDS tuner insertion with USB interface,  
for PA mixing amplifiers with insertion compartment.

- RDS function for FM
- 24 station presets (FM: 3 x 6, AM: 1 x 6)
- Station scanning
- USB storage media can be connected directly
- Reproduction of MP3 files and WMA files
- Display of file name
- Easy folder navigation
- Alphanumeric LCD
- Autorestart after power failure
- Memory for settings and operating modes

## Technical data:

Description	: FM/AM RDS tuner insertion
Media	: MP3, WMA
Frequency range	: -
THD	: < 0.5%
Channel separation	: -
Dynamic range	: -
S/N ratio	: -
Output, analogue	: -
Output, digital, U <sub>pp</sub>	: -
Power supply	: DC 17 V/250 mA
Mains voltage	: DC 17 V
Mains frequency	: -
Power consumption, operation	: -
Power consumption, standby	: -
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Dimensions	: 195 x 40 x 96 mm
Dim., player mech.	: -
Dim., control panel	: -
Weight	: 260 g
Connections	: USB
Packing dimensions (W x H x L)	: 0.22 x 0.175 x 0.06 m
Gross weight	: 0.46 kg