SA-130DMP - Amplifier





Stereo forstærker, med integreret MP3 afspiller (USB/SD), Bluetooth modtager og FM radio.

- Bluetooth modtager for trådløs tilslutning af smartphones eller tablets m.v.
- USB stik kan tilsluttes direkte
- Til SD-kort op til 32 GB (FAT16/FAT32), kan købes separat
- Justerbart mikrofon input og aux input på fronten
- Justerbart stereo line input
- Pre-amp main in, til for eksempel effektenheder, equalizere, feedback controllere
- 2-vejs tone kontrol
- Justerbart master output
- 482 mm (19") rack installation, 1 RS

MONACOR

Technical data:

Bluetooth	:	1
Peak output power	:	-
Power rating	:	130 W
Power rating at 2 Ohm	:	-
Power rating at 4 Ohm	:	2 x 75 W
Power rating at 8 Ohm	:	2 x 45 W
Power rating at 16 Ohm	:	-
Power rating at 100 V	:	-
Power rating with 4 Ohm bridged operation	:	-
Power rating with 8 Ohm bridged operation	:	-
Output impedance	:	-
Channels	:	2
Zones	:	-
Inputs	:	600 mV/30 kOhm (line) 2 mV/0.5 kOhm (mic) 370 mV/30 kOhm (aux) 950 mV/25 kOhm (amp in)

Attenuation factor	:	-
Frequency range	:	20-20,000 Hz
Crossover network	:	-
Crossover frequency	:	-
Integrated limiter	:	-
Equalizer bass	:	± 10 dB/100 Hz
Equalizer midrange	:	-
Equalizer treble	:	± 10 dB/10 kHz
S/N ratio	:	â‰¥ 80 dB
Crosstalk attenuation	:	â‰¥ 45 dB
THD	:	â‰¤ 0.1%
Phantom power	:	-
Mains voltage	:	∼ 230 V
Mains frequency	:	50 Hz
Power consumption, operation	:	320 VA
Power consumption, standby	:	-
Standby current	:	-
Operating voltage (possible alternative)	:	-

Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Width	: 482 mm

Height	: 44 mm
Depth	: 245 mm
Rack units, RU	: 1
Weight	: 5.62 kg
Connections	: 1 x RCA L/R (line), 1 x XLR/6.3 mm jack (mic), 1 x 3.5 mm jack (aux), 1 x RCA L/R (amp in), 1 x RCA L/R (amp out), screw terminals (speakers) with 4 mm banana jack

Packing dimensions (W x H x L)	: 0.3 x 0.11 x 0.53 m
Gross weight	: 6.42 kg
Net weight	: 5.85 kg